

TAROT 6S 380KV 4008							
电压 (V)	旋翼尺寸	电流 (A)	推力 (G)	功率 (W)	效率 (G/W)	转速 (RPM)	温度 (°C)
22.2V	1255	1	260	22.8	11.4	3180	
		2	420	45.6	9.2	4070	
		3	600	68.4	8.7	4630	
		4	720	91.2	7.8	5170	
		5	850	114	7.4	5520	
		6	940	136.8	6.8	5940	
		7	1120	159.6	7.0	6150	
		8	1170	182.4	6.4	6450	
		9	1250	205.2	6.0	6710	
		10	1330	228	5.8	6870	
		10.7	1420	243.9	5.8	7020	38

TAROT 6S 380KV 400S

电压 (V)	旋翼尺寸	电流 (A)	推力 (G)	功率 (W)	效率 (G/W)	转速 (RPM)	温度 (°C)
22.2V	1355	1	260	22.8	11.4	2980	
		2	460	45.6	10.0	3600	
		3	650	68.4	9.5	4230	
		4	770	91.2	8.4	4660	
		5	860	114	7.5	4970	
		6	980	136.8	7.1	5270	
		7	1090	159.6	6.8	5520	
		8	1180	182.4	6.4	5830	
		9	1310	205.2	6.3	5970	
		10	1380	228	6.0	6200	
		11	1440	250.8	5.7	6330	
		12	1530	273.6	5.5	6470	
		12.4	1620	282.7	5.7	6560	44